

BANDPASS FILTER

FB-0860



Features

- 3 dB Bandwidth, $\pm 7.5\%$
- Rejection Characterized by Chebyshev Transfer Function
- 5 Section Filter
- User defined option available

Specifications

Parameter	Min	Typ.	Max
Center Frequency, f_c (GHz)		8.6	
Passband (GHz)		$\pm 7.5\%$ of f_c	
Insertion Loss @ f_c (dB)			3
Return Loss in Passband (dB)	12	18	
Stopband Suppression (dB) beyond $\pm 20\%$ of f_c	25	30	
Stopband Suppression (dB) beyond $\pm 35\%$ of f_c	40	50	
Impedance (Ω)		50	
RF Power (W)			1

Part Number Options

Please specify connector configuration by adding to model number.					
Center Frequency (GHz)	Model number	Connector configuration ¹		Example	Outline
8.6	FB-0860	No dash (F-F)		FB-0860 -2K (K-Male in; K-Female out)	TE
User Defined	Contact factory	-1 (F-M)	S (SMA)		
		-2 (M-F)	K (2.92)		
		-3 (M-M)	V (2.40)		

¹Connectors are SMA Female by default.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.




Fig. 1. Magnitude response for a typical FB-0860.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.

© Marki Microwave, Inc.



215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com

www.markimicrowave.com