

LEAD-FREE / RoHS-COMPLIANT

HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

Features

- 200 kHz to 6 GHz Balun (Balanced to Unbalanced Transformer)
- Better than 37 dBm 1-dB compression point
- Tuned for Optimal Phase/Amplitude Balance
- Applications: Analog to Digital Converters, Balanced Receivers, Baseband Digital Modulation, Signal Integrity
- [BALH-0006.s3p](#)



Electrical Specifications - Specifications guaranteed from -55 to +100°C, measured in a 50Ω system.


Parameter	Frequency Range	Min	Typ	Max	
Insertion Loss as a mode converter (dB)	200 kHz to 6 GHz		4	5	
Input 1 dB Compression (dBm) ¹		37			
Nominal Phase Shift (Degrees)			180		
Amplitude Balance (dB)			0.1	0.5	
Phase Balance (Degrees)			1	5	
Common Mode Rejection (dB)			30	40	
Isolation (dB)				8	
VSWR (Input)				1.5	
VSWR (Output)				1.7	
Risetime /Falltime (ps) ²				11.5	
Weight (g)				27	

¹Measured in a well-heat sunk environment.

²Specified as 90%/10%. Calculated from $\tau_{\text{balun}}^2 = (\tau_{\text{out}}^2 - \tau_{\text{in}}^2)$

Model Number	Description
BALH-0006	200 kHz to 6 GHz High Power Balun with SMA connectors ¹ , LEAD-FREE/RoHS COMPLIANT

¹Default is SMA female connectors. Consult factory for other connector options.




HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

Page 2

Block Diagram



Single ended to differential

Differential to single ended




Fig. 1. Oscilloscope measurements of the BALH-0006 with a 10 Gb/s PRBS pattern. Bit pattern is measured with a 2^7-1 PRBS input demonstrating extremely good pulse fidelity for both inverted and non-inverted output. Eye diagrams are taken with a $2^{31}-1$ PRBS input demonstrating minimal eye distortion/closure afforded by the extremely low frequency operation of the balun (<200 kHz).

HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com

Typical Performance Scattering Parameters

Three port scattering parameters measured as three single-ended 50Ω ports showing relationship between any two ports. For example: S21 and S31, often referred to as insertion loss of a balun, is the output response on ports 2 and 3 with an input stimulus on port 1.




Fig. 2. Common to output port insertion loss and output to output port Isolation.




Fig. 3. Return loss for common port and output ports.




Fig. 4. Amplitude balance between output ports.




Fig. 5. Phase balance between output ports.





Fig. 6. Common mode rejection.

HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

Mixed Mode Scattering Parameters




Mixed mode scattering parameters are used to characterize differential circuits. For baluns, this means that the 0° and 180° ports become a single 100Ω differential port and the common port remains the same 50Ω common port. The two-port s-parameters of the balun are then characterized based on differential (d), common mode (c), or single-ended (s) signals. For example: S12ds is the differential output response given a single ended input.



HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

215 Vineyard Court, Morgan Hill, CA 95037 | Ph: 408.778.4200 | Fax 408.778.4300 | info@markimicrowave.com






HIGH POWER BALUN (200 kHz to 6 GHz)

BALH-0006

Page 6

DC Interface

Port	Description	DC Interface Schematic
Common Port / In (Unbalanced)	The common port is DC short to ground.	 Common Port (Unbalanced)
Out 1 / 0° Port (Balanced)	The 0° port is DC short to ground.	 0° Port (Balanced)
Out 2 / 180° Port (Balanced)	The 180° port is DC short to ground.	 180° Port (Balanced)

Revision History

Revision code	Revision Date	Comment
-	2014	Datasheet initial Release
A	October 2019	Mixed Mode Scattering Parameters added
B	November 2019	RoHS Compliant assembly
C	July 2020	Specs table update

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.