

HIGH POWER BIAS TEE

BT2-0026

The BT2-0026 is constructed using a custom-made, resonance-free conical inductor to achieve extremely broadband performance. By minimizing the overall inductor size and using proprietary packaging techniques, the BT2-0026 is a superior option in terms of performance, reliability and ease-of-use when compared to cumbersome user-designed bias tees employing off-the-shelf conical inductors. The extremely low cutoff and resonance free operation makes the BT2-0026 suitable for biasing amplifiers, lasers, and modulators driven with high frequency data patterns.




Features

- Broadband: 100 kHz to 26.5 GHz
- Low Insertion Loss
- High Power
- Non-Resonant
- Compact Size


Electrical Specifications - Specifications guaranteed from -55 to +100°C, measured in a 50Ω system.

| Parameter | Frequency Range | Min | Typ | Max |
|--------------------------------------|------------------|-----|-----|-----|
| Insertion Loss (dB) | 300 kHz-26.5 GHz | | 1 | 2 |
| | 100-300 kHz | | 2 | |
| DC Port Isolation (dB) | 100 kHz -1 GHz | | 50 | |
| | 1-26.5 GHz | | 30 | |
| Return Loss (dB) | 100 kHz-26.5 GHz | | 14 | |
| RF Power (W) | | | | 10 |
| DC Current (A) | | | | 2 |
| DC Voltage (V) | | | | 50 |
| DC Resistance (Ω) | | | 0.5 | |
| Risetime /Falltime (ps) ¹ | | | 10 | |

¹Specified as 90%/10%. Calculated from $\tau_{bt}^2 = (\tau_{out}^2 - \tau_{in}^2)$



Schematic



Application Examples




Fig. 1. Example Schematics of a) Broadband Microwave Amplifier Biasing, b) Laser/LED Biasing for Data Communication and c) Mach-Zender Modulator Biasing for Data Communication

Typical Performance




Fig. 2. RF insertion loss.




Fig. 3. Return loss.




Fig. 4. Low frequency RF response.




Fig. 5. Low frequency isolation.




Fig. 6. DC-RF isolation.




Fig. 7. Near DC isolation




Fig. 8. Group delay.




Fig. 9. Performance over temperature

HIGH POWER BIAS TEE

BT2-0026

Page 4




Fig. 7. Oscilloscope measurements of the BT2-0026 with a 10Gb/s PRBS pattern. Eye diagrams are taken with a $2^{31}-1$ PRBS input demonstrating minimal eye distortion/closure afforded by the extremely low frequency operation of the bias tee.

| Model Number | Description |
|--------------|--|
| BT2-0026 | 100 kHz to 26.5 GHz High Power Bias Tee with SMA connectors ¹ |

¹Consult factory for other connector options.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.