

## WILKINSON POWER DIVIDER

**PD-0218**

### Features

- 2 to 18 GHz In-phase Power Splitting
- 22 dB Typical Output to Output Isolation
- Outstanding Phase and Amplitude Balance
- [Microwave Power Dividers & Couplers App Note](#)



**Electrical Specifications** - Specifications guaranteed from -55 to +100°C, measured in a 50Ω system.

Parameter <sup>1</sup>	Frequency Range (GHz)	Min	Typ	Max	
Nominal Power Splitting (dB)	2 to 18		3		
Nominal Phase Shift (Degrees)			0		
Amplitude Balance (dB)			±0.2	±0.75	
Phase Balance (Degrees)			±2	±10	
Excess Insertion Loss (dB) <sup>2</sup>			1	2	
VSWR				1.25	1.6
Isolation (dB)			15	22	
Power (W)					1
Weight (g)				45	



<sup>1</sup>Specifications guaranteed when operated in a 50Ω system.

<sup>2</sup>Excess Insertion Loss = (Common Port to Output Port Insertion Loss) – 3 dB.

Model Number	Description
PD-0218	2 - 18 GHz Power Divider with SMA connectors <sup>1</sup>

<sup>1</sup>Default is SMA female connectors. Consult factory for other connector options.

Port	Connector Type
Input	SMA Female
Output x2	SMA Female



**Typical Performance**




Fig. 1. Common port to output port insertion loss.




Fig. 2. Return loss for output and common ports.




Fig. 3. Amplitude balance between output ports.




Fig. 4. Phase balance between output ports.




Fig. 5. Isolation between output ports.

Marki Microwave reserves the right to make changes to the product(s) or information contained herein without notice. Marki Microwave makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Marki Microwave assume any liability whatsoever arising out of the use of or application of any product.